



Brady Driver Installation Guide

Copyright and Trademarks

Disclaimer

This manual is proprietary to **Brady** Worldwide, Inc. (hereafter "**Brady**"), and may be revised from time to time without notice. **Brady** disclaims any understanding to provide you with such revisions, if any.

This manual is copyrighted with all rights reserved. No portion of this manual may be copied or reproduced by any means without the prior written consent of **Brady**.

While every precaution has been taken in the preparation of this document, **Brady** assumes no liability to any party for any loss or damage caused by errors or omissions or by statements resulting from negligence, accident, or any other cause. **Brady** further assumes no liability arising out of the application or use of any product or system described, herein; nor any liability for incidental or consequential damages arising from the use of this document. **Brady** disclaims all warranties of merchantability of fitness for a particular purpose.

Brady reserves the right to make changes without further notice to any product or system described herein to improve reliability, function, or design.

Trademarks

All brand or product names referenced in this manual are trademarks (™) or registered trademarks (®) of their respective companies or organizations.

© 2018 **Brady Worldwide, Inc.** All Rights Reserved.

Version 4.x

Revision A

Brady Corporation
6555 West Good Hope Road
P.O. Box 2131
Milwaukee, WI 53201-2131
www.bradycorp.com

Technical Support

Contact Information

For technical assistance, locate your regional Brady Technical Support office by going to:

- **Americas:** www.bradyid.com/techsupport
- **Europe:** www.bradyeurope.com/services
- **Asia Pacific:** www.brady.co.uk/landing-pages/global-landing-page
- **Australia:** www.bradyid.com.au/en-au/supportlanding
- **Canada:** www.bradycanada.ca
- **Latin America:** www.bradylatinamerica.com

Introduction

If Brady Workstation is used for creating labels, the drivers will automatically be installed on the computer. If LabelMark™ or any third party software is being used, the drivers will need to be manually installed.

If Bonjour is not installed on your machine and is supported by your printer, it will be installed as a part of the setup process.

Communication Configuration

If your Brady printer has built-in networking, you can configure the printer to run as a network printer through Ethernet or WiFi or as a local printer (physically attached to your computer via a USB cable). To establish the printer as a network printer, you must configure the printer to recognize and work with your networks. The Brady printer drivers may be contained on a CD that is packaged with your printer, otherwise they can be downloaded from Brady's websites: www.bradyid.com or www.bradyeurope.com.

The printer driver installation identifies two different installation scenarios:


- Ethernet or WiFi printing (network printer)
- USB driver only (local printer)

Network (WiFi or Ethernet) Installation


Use this installation process if you intend to send print jobs to the printer from the computer over a network. The printer must have WiFi or Ethernet support in order to use this installation method. Check the User Manual if you are unsure of the printer's capability.

If the printer did not come with a printer driver CD and you have not already downloaded the drivers from Brady's website, please do so now.

1. Either insert the printer driver CD into the computer or double-click on the printer driver that you downloaded.
2. Select the **desired language** from the drop-down menu, then click **Next**.




3. Click **Install**.



4. Select the **printer model** for which printer drivers are being installed and click **Next**.




5. Power up the printer, if necessary.
6. Select **Wireless or Ethernet network connection** and click **Next**.




7. Follow the instructions in your printer's user manual for setting up the network connection.
8. Refer to the connection guidelines, shown below, to verify that the printer and PC are on the same network.


Connecting using a router (e.g., at home)



Connecting using an Ethernet network (e.g., at the office)




9. Follow the **on-screen instructions**, then click **Next**.




The Bonjour program is designed to establish and monitor network printers. The Bonjour installation screens will not display if Bonjour is already installed on your computer. To learn more about Bonjour print services for Windows, click the link in the *Installing Bonjour Print Services* screen. Click Back to return to the License Agreement screen.

10. Read the Apple End User License Agreement, click *I accept the terms in the license agreement* and then click **Next**.



11. If Bonjour is supported by your printer, choose your **printer's name** from the list and click **Next**.

Note: If the computer can communicate with the printer over both WiFi and Ethernet it will randomly choose one of those connections. If you wish to specify the connection - WiFi or Ethernet - *either* continue to the next step *or* disconnect the printer from the undesired interface and move to step 11.




12. If the printer does not support Bonjour or you chose to add the printer manually, enter the printer's IP address or hostname and click **Next**.

13. Enter a **name** for the printer using up to 12 alphanumeric characters, then click **Next**.

Note: Printer name will only be seen on the computer on which the drivers are being installed.

A progress bar will display while the printer driver is being installed.

14. Click **Finish** on the Installation Complete Screen.




Installing the USB Driver Only


IMPORTANT! Use this installation process if you intend to send print jobs to the printer from a PC using a USB cable only.

To install the printer driver for your Brady printer perform the following steps:

1. Either insert the printer driver CD into the computer or double-click on the printer driver that you downloaded.
2. Select the **desired language** from the drop-down menu, then click **Next**.




3. Click **Install**.



4. Select the **printer model** for installation and click **Next**.



5. Power up the printer, if necessary.
6. Select **Using USB cable only** and click **Next**.




7. Follow the **on-screen instructions**, then click **Next**.

Note: A message displays when the USB cable is connected. The printer driver installs automatically.

A progress bar will display while the printer driver is being installed.

8. Click **Finish** on the Installation Complete Screen.



USB Connection Failed

The USB connection could fail for the following reasons:

- The printer is powered OFF.
- The USB cable is not connected.
- The USB driver install was not completed.

Printer Status Failed

If the printer status indicates Failed:

1. Ensure the printer is powered ON.
2. Ensure the cable is securely and correctly plugged into the port.

OR

Disconnect the USB cable from the PC and try another port.

3. Click Back and try again.

